

DS-PM1-I16O2-WE Multi IO Transmitter



DS-PM1-I16O2-WE wireless multi IO transmitter offers a connection of third party wired detectors like outdoor PIR, to AX PRO alarm system, the alarm types and zone parameters can be set through APP by installers easily. Under the situation when your want to update your security system to AXPRO with more innovated features, multi IO transmitter gives you a chance to rebuild your alarm system without changing existing wired detectors.

- 868 MHz two-way wireless communication
- LED display, show the real status of device
- With 16 onboard inputs and 2 outputs, can be applied to connect wired detectors
- With two 12 V power outputs, can be used to power up external wired detectors
- Large space for back up storage battery



▪ Specification

Software features	
End of Line Resistance	1k 2.2k 4.7k 8.2k NO/NC
Hardware features	
Serial port	1
Battery port	1, 12 VDC input
Tamper-Proof	Front and rear
Power switch	1
Alarm input	16
Alarm output	2
Power Output	2 (12 V, total1 A)
Electrical characteristics	
Battery type	Compatible with 12 V 7 Ah 150 × 64 × 94 mm
Power supply	100-240 VAC, 30 W
Operation humidity	10% to 90%
Operation temperature	−10 to 40°C
Power consumption	Battery Supply: Quiescent current (50 mA), Max current (1500 mA), Voltage (13.8 V) 220 V Supply: Quiescent current (45 mA), Max current (300 mA), Voltage (220 V)
Battery life span	Up to 36 hours
Wireless transmission	
RF frequency	868 MHz
RF method	Two-way communication
RF modulation	2GFSK
RF distance	1100 m
Display	
Indicator	3: Power(Green), Fault(Amber), Signal Strength(Green/Red)
General	
Installation method	Wall Mounting
Dimension(W × H × D)	261 × 199 × 86.4 mm
Shell material	Plastic
Color	White
Weight	975 g (without battery)

▪ Available Model

DS-PM1-I16O2-WE

Distributed by



HIKVISION

Headquarters

No.555 Qianmo Road, Binjiang District,
Hangzhou, 310051, China
T +86-571-8607-5008
overseasbusiness@hikvision.com

Hikvision USA
T +1-909-865-0400
sales.usa@hikvision.com

Hikvision Australia
T +61-2-8593-4233
salesau@hikvision.com

Hikvision India
T +91-22-28469800
sales@pmahikvision.com

Hikvision Canada
T +1-800-380-6890
sales.canada@hikvision.com

Hikvision Thailand
T +662-275-3646
sales.thailand@hikvision.com

Hikvision Europe
T +31-23-3642770
sales.eu@hikvision.com

Hikvision Italy
T +39-0439-6802
info.it@hikvision.com

Hikvision Brazil
T +55 11 3315-0850
latam.support@hikvision.com

Hikvision Turkey
T +90 12160217070-7074
sales.tr@hikvision.com

Hikvision Malaysia
T +601-7652-2413
sales.my@hikvision.com

Hikvision UK & Ireland
T +41520-902140
sales.uk@hikvision.com

Hikvision South Africa
T +27 11 01 0361172
sales.africa@hikvision.com

Hikvision France
T +33 01-85-330-450
info.fr@hikvision.com

Hikvision Kazakhstan
T +7-727-8730667
nikitapantikov@hikvision.ru

Hikvision Vietnam
T +84-974270898
sa.cau.vi@hikvision.com

Hikvision UAE
T +971-4-4432090
sales.me@hikvision.com

Hikvision Singapore
T +65-6884-4718
sg@hikvision.com

Hikvision Spain
T +34-91-737-16-55
info.es@hikvision.com

Hikvision Tashkent
T +99-87-1238-9432
info@hikvision.ru

Hikvision Hong Kong
T +852-2151-1761
info.hk@hikvision.com

Hikvision Russia
T +7-495-660-67-00
sales.ru@hikvision.com

Hikvision Korea
T +82-10151-731-8617
sales.korea@hikvision.com

Hikvision Poland
T +48-22-463-01-50
info.pl@hikvision.com

Hikvision Indonesia
T +62-21-2932759
Sales.indonesia@hikvision.com

Hikvision Colombia
sales.colombia@hikvision.com