

DS-PKA-WLM Wireless Keypad

The DS-PKA-WLM series wireless keypad can connect to security control panel for alarm control and operation. It can also notice alarm by indicator and buzzer.



A decorative geometric pattern consisting of several overlapping, semi-transparent triangles in shades of gray, located on the left side of the page.

Available Models

DS-PKA-WLM

Features

- 433/868 MHz two-way wireless communication
- AES-128 encryption
- Operation: Arming, disarming, alarm clearing, etc.
- Arming or disarming with card
- Patrol card (different from the arming/disarming card) checking in
- Full touch screen design with LED backlight

Specifications

Model	DS-PKA-WLM-433	S-PKA-WLM-868
RF	RF speed	10.0 kbps/4.8 bps
	RF frequency	433 MHz/868 MHz
	RF modulation	2GFSK
	RF distance	800 m (open area)
	RF power	10 dBm
	TAMPER switch	1
Interface & component	RF module	Communicates with wireless control panel
	Card	Supports standard IC card swiping
	Buzzer	1
	Serial port	1, reserved
	Numeric	10 keys: 0 to 9
Application & protocol	Function key	6 function keys: fire alarm, away arming, stay arming, disarming, delete, and confirm
	Protocol	HIK wireless protocol: Access to wireless control panel, two-way communication
	Power	3 VDC power input
Electrical & battery	Battery type	4 AA batteries
	Battery life span	3 years
	Operation humidity	10% to 90% (No condensing)
Others	Operation temperature	-10 °C to +55 °C (-4 °F to +122 °F)
	Color	White
	Dimension	φ131.5 mm (5.2"); height: 23 mm (0.9")

Distributed by



HIKVISION

Headquarters

No.555 Qianmo Road, Binjiang District,
Hangzhou 310051, China
T +86-571-8607-5008
overseasbusiness@hikvision.com

Hikvision USA
T +1-909-985-0400
sales.usa@hikvision.com

Hikvision Australia
T +61-2-9599-2233
sales.au@hikvision.com

Hikvision India
T +91-22-28409900
sales@primahikvision.com

Hikvision Canada
T +1-888-310-0390
sales.canada@hikvision.com

Hikvision Thailand
T +662-275-9946
sales.thailand@hikvision.com

Hikvision Europe
T +31-23-3542770
sales.eu@hikvision.com

Hikvision Italy
T +39-0439-9802
info.it@hikvision.com

Hikvision Brazil
T +55-11-3316-0850
latam.support@hikvision.com

Hikvision Turkey
T +90-2163217070-7074
sales.tr@hikvision.com

Hikvision Malaysia
T +601-7852-2413
sales.my@hikvision.com

Hikvision UK & Ireland
T +41828-902140
sales.uk@hikvision.com

Hikvision South Africa
Tel: +2711010361172
sales.africa@hikvision.com

Hikvision France
T +33(0)1-85-330-450
info.fr@hikvision.com

Hikvision Kazakhstan
T +7-727-8730667
nikolapavlov@hikvision.kz

Hikvision Vietnam
T +84-974270898
sales.viet@hikvision.com

Hikvision UAE
T +971-4-4432090
sales.me@hikvision.com

Hikvision Singapore
T +65-6884-4718
sg@hikvision.com

Hikvision Spain
T +34-91-737-16-65
info.es@hikvision.com

Hikvision Tashkent
T +99-87-1238-9438
info@hikvision.uz

Hikvision Hong Kong
T +852-2151-1761
info.hk@hikvision.com

Hikvision Russia
T +7-495-660-67-80
sales.ru@hikvision.com

Hikvision Korea
T +82-0032-731-8217
sales.korea@hikvision.com

Hikvision Poland
T +48-22-483-01-50
info.pl@hikvision.com

Hikvision Indonesia
T +62-21-2933759
Sales.indonesia@hikvision.com

Hikvision Colombia
sales.colombia@hikvision.com